

**DIESEL GENRETOR SET ,50HZ.,400/230V.,415/240V.,1500RPM
TV. SERIES -- VOLVO PENTA 85 - 770 KVA.**

Model	Volvo Penta	Standby		Prime	
		KVA.	KW	KVA.	KW
TV90	TD520GE	94	75	85	68
TV115	TAD531GE	112	89	101	81
TV145	TAD532GE	144	115	130	104
TV165	TAD731GE	170	136	154	123
TV200	TAD732GE	202	162	183	146
TV220	TAD733GE	226	180	205	164
TV275	TAD734GE	280	224	255	204
TV350	TAD1341GE	351	281	319	255
TV385	TAD1342GE	387	310	352	282
TV410	TAD1343GE	414	331	378	302
TV450	TAD1344GE	452	362	411	329
TV500	TAD1345GE	506	405	456	365
TV550	TAD1641GE	556	445	505	404
TV650	TAD1642GE	651	521	591	473
TV700	TWD1643GE	700	560	630	504
TV715	TWD1644GE	717	573	652	521
TV770	TWD1645GE	770	616	700	560

REMARK

Standby Power: Standby duty-operation under variable charge 500h/year with overcharge-for continuous use, derated 10 %

Prime Power: Continuous duty 24/24 H under variable load-10% overcharge acceptable 1h/12h

